



Qtron 's MaxiBas is a brilliant smart home system, controlling air conditioners, lighting and security alarm systems or any household appliances through mobile phone, PC or keypad.

That's why Otron 's MaxiBas gives you home control in the palm of you hand.

Qtron®'s MaxiBAS features:

- 16 zones expandable to 64 zones
- Capability of dividing a security system into 32 partitions
- Able to store up to 192 useer passwords (PIN) in the system
- Reporting to 16 commom telephones numbers with messages from synthesizer (up to 16 messages)
- Possibility of timing control by using 64 timers, which can be pre-programmed for weekly schedule
 of work and for specified periods of exceptions.
- Each zone has its own timer (daily or weekly) programmed by users, ensuring automatic arming and disarming

Qtron®

Building Controls Specialist

- · High capacity event buffer (6000 events) in which, in addition to monitor events
- Additional functions of RS232 ports which allowed PC monitoring and system configurations
- Remote Monitoring:
- With map of a real site (bmp file) to monitor the status of the system
- Controllable with virtual keypad
- User phone or PC to activate / deactivate air condition, llighting, security and home appliances
- Integrated with proximity card readers that allow flexible configurations
- CMS ready (Contact ID, Silent Knight, Radionix & etc) with 2 stations number programmable
- Allow integration of additional panel which includes:
- Partition keypad
- Coded lock / Access keypad
- LCD messages keypad
- Synoptic board for visual information on the status of 64 zones and 32 partitions of alarm system
- Sub-control panel module
- Outputs module
- Outputs module with power supply
- Inputs module
- Inputs module with power supply
- Proximity card reader
- Voice synthesizer expander
- GSM module

Authorised Dealer:

